


## Keyboard Shortcuts:

<b>alt-Z</b>	CANCEL any paste operation that is in progress	<i>(also a menu item)</i>
<b>alt-A</b>	clear ring buffer (256k buffer used for serial input)	<i>(also a menu item)</i>
<b>alt-C</b>	clear graphics layer	<i>(also a menu item)</i>
<b>alt-D</b>	clear text layer	<i>(also a menu item)</i>
<b>alt-P</b>	paste from clipboard	<i>(also a menu item)</i>
<b>alt-L</b>	STOP/RESUME logging	<i>(also a menu item)</i>
<b>alt-R</b>	RESET terminal	<i>(also a menu item)</i>
<b>alt-&gt; and &lt;</b>	bell volume level up and down	
<b>alt-U</b>	hide/show cursor	
<b>alt-B</b>	send break, signals 1455 firmware to reset Micromite	
<b>alt-ENTER</b>	send CR + LF character sequence	
<b>alt-ZERO</b>	send null character (also <b>ctrl-ZERO</b> for VT102 compatibility)	
<b>alt-1 to 4</b>	set/clear modem control (DTR/RTS) outputs	
<b>alt-6</b>	scroll screen and cursor up, until the cursor is at the top line	
<b>alt-7</b>	control input – enter mixed text and control characters to send as a string	
<b>alt-8</b>	pause output to screen, serial input is buffered until un-paused	
<b>ctrl-SPACE</b>	try to restore last valid connection, or disconnect if already connected	



NOTE: with most LINUX keyboards, pressing ctrl-3 to ctrl-7 will produce the control characters between 27<sub>10</sub> and 31<sub>10</sub>. This saves trying to remember the more cryptic 'official' keys for each:

27 <sub>10</sub>	ctrl-3	[	
28 <sub>10</sub>	ctrl-4	\	
29 <sub>10</sub>	ctrl-5	]	
30 <sub>10</sub>	ctrl-6	~ or ^	(both are shifted)
31 <sub>10</sub>	ctrl-7	/ or _	(underscore shifted)

## Status Line:

Above the terminal screen area is a status line that displays various useful pieces of information about the terminal session. This includes last ASCII character displayed and key pressed, current cursor location, timing information, and various status indicators:

```
00 row=01 col=01 key=00 00.0s 00.0s 00% online logging [000000] DTR RTS CTS dsr
1. 2. 3. 4. 5. 6. 7. 8. 9. 10. 11.
```

1. last ASCII character displayed
2. cursor position, current row
3. cursor position, current column
4. last ASCII key pressed
5. time since last serial data received
6. time since last serial data transmitted
7. percentage of ring buffer in use
  - silver <10% used
  - blue 10% to 39% used
  - yellow 40% to 69% used
  - red >70% used
8. online annunciator - green when connected to a serial port
9. logging annunciator - yellow when logging to a file
10. number of characters waiting to be pasted:
  - green fast paste
  - blue slow paste
11. status of modem control lines. DTR and RTS controlled from keyboard:
  - UPPERCASE line is set (asserted)
  - lowercase line is clear